

## High Gain Directional LTE/CBRS Antenna 698-2700/3300-4200 MHz, 2x2 MIMO



- High Gain Directional Antenna supporting 698-2700 & 3300-4200 MHz.
- Suitable for indoor/outdoor networks operating in the LTE, GSM, CDMA, PCS, 3G and 4G frequency ranges.
- Ideal for outdoor voice and data deployments in remote, rural, industrial, and donor antenna deployments.
- Rugged construction provides protection from sun, wind, rain, snow, and dust.


Connector Option	Product SKU	Ventev Part #
N Female	240174	M3070090D21206
4.3-10 Female	230065	M3070090D21249

Electrical Specifications				
Frequency Bands, MHz	698–960	1710–2700	3300-4200	
Polarization		±45°		
Azimuth (HBW)	70°	65°	60°	
Elevation (VBW)	65°	60°	55°	
VSWR	≤2.0	≤2.0	≤2.0	
Gain, dBi	7	7.5	8	
Front-to-Back Ratio, dB	≥15	≥15	≥20	
PIM, IM3, 2x20W (43dBm), dBc	-153	-153	-	
Max Input Power per Port, watts		50		
Impedance, ohm		50		
Mechanical Specifications				
Product Dims	12.6 x 8.3 x 3 in (323 x 205 x 70 mm)			
Input Connector & Pigtail	2x N-type	or 4.3-10 Female, 12" leads F	RG141	
Radome		White, UV Resistant ABS		
Mounting & Bracket	•	2.0" OD); Bracket and hardw Wall hardware supplied by c		
Wind Survival		134 mph		
Operating Temperature		-40 °F to +158 °F		
Relative Humidity	Up to 95%			
Product Weight	1.5 Kg (3.3 lb)			


Every Ventev antenna is RoHS compliant and covered by company's 2-year warranty program.



## High Gain Directional LTE/CBRS Antenna 698-2700/3300-4200 MHz, 2x2 MIMO



## **Installation Sketch**



1 Antenna 2 L bracket (1×) 3 Mounting clamps (2×) 4 U Bolts – M6 (2×) 5 Flat washers – M6 (4×) 6 Split-lock washers – M6 (4×) 7 Hex nuts – M6 (4×) 8 Hex nuts – M6 (2×) 9 Split-lock washers – M6 (2×) 10 Flat washers – M6 (2×) 11 Wall mount screws – M4 (4×) 12 Wall mount pad 13 Plastic anchor (4×)		
3 Mounting clamps (2×) 4 U Bolts – M6 (2×) 5 Flat washers – M6 (4×) 6 Split-lock washers – M6 (4×) 7 Hex nuts – M6 (4×) 8 Hex nuts – M6 (2×) 9 Split-lock washers – M6 (2×) 10 Flat washers – M6 (2×) 11 Wall mount screws – M4 (4×) 12 Wall mount pad	1	Antenna
4 U Bolts – M6 (2×)  5 Flat washers – M6 (4×)  6 Split-lock washers – M6 (4×)  7 Hex nuts – M6 (4×)  8 Hex nuts – M6 (2×)  9 Split-lock washers – M6 (2×)  10 Flat washers – M6 (2×)  11 Wall mount screws – M4 (4×)  12 Wall mount pad	2	L bracket (1×)
5 Flat washers – M6 (4×) 6 Split-lock washers – M6 (4×) 7 Hex nuts – M6 (4×) 8 Hex nuts – M6 (2×) 9 Split-lock washers – M6 (2×) 10 Flat washers – M6 (2×) 11 Wall mount screws – M4 (4×) 12 Wall mount pad	3	Mounting clamps (2×)
6 Split-lock washers – M6 (4×) 7 Hex nuts – M6 (4×) 8 Hex nuts – M6 (2×) 9 Split-lock washers – M6 (2×) 10 Flat washers – M6 (2×) 11 Wall mount screws – M4 (4×) 12 Wall mount pad	4	U Bolts – M6 (2×)
7 Hex nuts – M6 (4×)  8 Hex nuts – M6 (2×)  9 Split-lock washers – M6 (2×)  10 Flat washers – M6 (2×)  11 Wall mount screws – M4 (4×)  12 Wall mount pad	5	Flat washers – M6 (4×)
8 Hex nuts – M6 (2×) 9 Split-lock washers – M6 (2×) 10 Flat washers – M6 (2×) 11 Wall mount screws – M4 (4×) 12 Wall mount pad	6	Split-lock washers – M6 (4×)
9 Split-lock washers – M6 (2×) 10 Flat washers – M6 (2×) 11 Wall mount screws – M4 (4×) 12 Wall mount pad	7	Hex nuts – M6 (4×)
10 Flat washers – M6 (2×) 11 Wall mount screws – M4 (4×) 12 Wall mount pad	8	Hex nuts – M6 (2 $\times$ )
11 Wall mount screws – M4 (4×) 12 Wall mount pad	9	Split-lock washers – M6 (2 $\times$ )
12 Wall mount pad	10	Flat washers – M6 (2 $ imes$ )
'	11	Wall mount screws – M4 (4 $\times$ )
13 Plastic anchor (4×)	12	Wall mount pad
	13	Plastic anchor $(4\times)$

Every Ventev antenna is RoHS compliant and covered by company's 2-year warranty program.