

4.9-5.85 GHz 3-Way Splitter with N-Style Jack Connector

TerraWave's antenna splitters are designed to divide or "split" the RF signal from one radio to multiple antennas. The splitters are perfect for applications that require coverage of two different areas with a single access point or bridge.

TerraWave's splitters are designed for the 5 GHz marketplace. The units' rugged design and small footprint make them ideal for most bridging and LAN applications.

Note: Requires two splitters per AP when using diversity



Features and Benefits:

- Provide RF coverage in separate areas with a single access point or bridge
- Compact, lightweight design
- Easy to mount
- High isolation, low insertion loss and minimal VSWR
- N-Style Jack connector included
- Excellent value—Superior performance at a competitive price

Specifications

Model	RMFLT-3-5800N
Frequency Range	4.9 ~ 5.85 GHz
Insertion Loss	≤ 7 dB
Isolation	≥ 20 dB
VSWR	≤ 1.8
Impedance	50 Ω
Maximum Power	50 Watts
Connector	N-Style Jack
Operating Temperature Range	-22°F ~ 140°F
Humidity	5% ~ 95 %
Dimensions	2.8" x 2.4" x 0.8"
Weight	5.29 ounces